


7. Part Names



No.	Name	Function
(1)	POWER LED (green)	Turns on when the unit power is turned on.
(2)	COM LED (green)	Illuminated: After startup, before IO-Link communication is established 1 second on 0.1 second off: IO-Link communication established 0.55 second on 0.55 second off: Find me 0.1 second on 0.1 second off: IO-Link communication cutoff
(3)	ERROR LED (Red)	Turns on when IO-Link communication stops or some other error occurs.
(4)	Input type LED (orange)	Turns on/off based on the type of analog input for each channel. 1 to 5 V is displayed as 0 to 5 V, and 4 to 20 mA is displayed as 0 to 20 mA.
(5)	Analog input terminal block (V+, GND, I+, GND)	Connects analog input signals (V+=0 to 3, I+=0 to 3, GND) and the shield wire (SLD) to the analog output device.
(6)	Analog output device power supply terminal block (L+, M)	Used to supply 24 V power (L+, M) to the analog output device.
(7)	Power terminal block (0 V, +24 V)	Supplies unit power (+24 V, 0 V) and I/O power (L+, M). This seven-pole removable connector has a pitch of 5.08 mm and a rating of 12 A. It uses AWG 24 to 12 wires. It is wired in parallel with the input power supply. Unit power (+24 V, 0 V) and C/Q are wired to the IO-Link master, and unit power is supplied by the IO-Link master. Unit power (+24 V, 0 V) and C/Q are connected internally with the terminals of the e-CON socket, and either the power terminal block or e-CON socket can be connected to the IO-Link master.
(8)	e-CON socket (4-pole)	Unit power (+24 V, 0 V) and C/Q can be wired to the IO-Link master via the e-CON socket.
(9)	DIN rail mounting hook	Slides for attaching/removing the product to/from the DIN rail.

8. Specifications

General Specifications

Item	Specifications
Power supply voltage	24 VDC +/-15% ^{*1}
Current consumption	50 mA max. (for 24 VDC)
Operating temperature	0 to +55°C (no freezing)
Operating humidity	5 to 95% RH (no condensation)
Storage temperature	-25 to +75°C (no freezing)
Storage humidity	5 to 95% RH (no condensation)
Vibration resistance	IEC 61131-2 compliant
Shock resistance	IEC 61131-2 compliant
Atmosphere	No corrosive gas
Operating altitude	0 to 2000 m
Installation location	In door use
Degree of protection	IP20
Measurement category	II or lower
Pollution degree	2 or lower
Applicable regulations	EMC EMC Directive (2014/30/EU) Environment RoHS Directive (2011/65/EU), China RoHS (Regulation 32)
Applicable standard	EN 61131-2 (Zone A)
Company standards	Noise resistance: Feilen Level 3 cleared
Compatible DIN rail	TH35-7.5Fe, TH35-7.5AI
Cable length	Maximum 20m (between IO-Link master and remote I/O unit)
Compatible wire	Power terminal block: AWG 24 to 12 Input terminal block: AWG 28 to 16
Material	Unit: PC, DIN rail mounting hook: POM, Terminal block: PA
Weight	Approx. 105 g (including terminal blocks, when not wired)
Included accessories	Instruction manual (this document), input terminal block: two pieces, power terminal block: one piece

^{*1} Use a Class 2 power supply or a power supply compliant with SELV (Safety Extra-Low Voltage) circuit and LIM (Limited Energy Circuit) circuit standards.

IO-Link Specifications


Item	Specifications
Host communication interface	IO-Link (operates as device)
Process input data byte count	8 bytes
Process output data byte count	1 byte
Minimum cycle time	0.7 ms
IO-Link revision	1.1
Communication speed	COM3 (230.4 kbps)
Communication function	IO-Link power supply

Analog input Specifications

Item	Specifications
Number of Input channels	4 CH
Type of analog input	Voltage (0 to 10 V, -10 to 10 V, 0 to 5 V, 1 to 5 V)/ Current (0 to 20 mA, 4 to 20 mA) switchable for all channels (Default value: Switched by process output data)
Maximum input voltage	±11 V
Maximum input current	24 mA
Voltage input equivalent impedance	250.5 k ohm
Current input equivalent impedance	246 ohm
Voltage accuracy	±0.30% of F.S. (at ambient temperature of 25°C) [*] Temperature coefficient (typical): ±80ppm/°C (0.008%/°C)
Current accuracy	±0.30% of F.S. (at ambient temperature of 25°C) Temperature coefficient (typical): ±110ppm/°C (0.011%/°C)
Input resolution	16 bits
Dielectric withstand voltage	500 VAC for one minute between I/O terminal batch and IO-Link batch.
Insulation resistance	10 Mega ohm or higher between all I/O terminals and IO-Link terminals at 500 VDC
Inter-channel isolation	None (common)
Insulation method	Photocoupler insulation

^{*}1: Accuracy when the type of analog input is set to 0 to 10 V or -10 to 10 V. Full scale is calculated as 10 V even when 0 to 5 V or 1 to 5 V is set.

9. Circuit Diagram



10. Process Data

The process data exchanged by the product with the IO-Link master using IO-Link cyclic communication is as follows.

IO-Link process data is transferred in big endian format. The table below is also in big endian format.

The IO-Link master UR series from OPTEX FA transfers IO-Link process data converted into little endian format to the host network by default, so the byte order will be the reverse of that in the table below.

Process data	Byte	bit 7	bit 6	bit 5	bit 4	bit 3	bit 2	bit 1	bit 0
Process input data ¹	+0	Channel 3 Analog input upper byte							
	+1	Channel 3 Analog input lower byte							
	+2	Channel 2 Analog input upper byte							
	+3	Channel 2 Analog input lower byte							
	+4	Channel 1 Analog input upper byte							
	+5	Channel 1 Analog input lower byte							
	+6	Channel 0 Analog input upper byte							
	+7	Channel 0 Analog input lower byte							
Process output data	+0	Channel 3 Input type	Channel 2 Input type	Channel 1 Input type	Channel 0 Input type				
	0: 0 to 10 V, 1: -10 to 10 V, 2: 0 to 5 V, 3: 0 to 20 mA								

^{*1} If the analog input value drops below the lower limit in the 1 to 5 V input or 4 to 20 mA input, the process input data will be 32768 (0x8000).

^{*2} When index number 74 ("Type of analog input") of the service data is "0", this designation by process output data is valid. Note that the process input data is fixed at 0 to 10 V input for "1", -10 to 10 V input for "2", 0 to 5 V input for "3", 1 to 5 V input for "4", 0 to 20 mA input for "5", and 4 to 20 mA input for "6".

11. Service Data

The service data for this product that can be read and written via IO-Link ISDU handling is as follows.

Name	Index number	Subindex number	Read/Write ^{*1}	Backup Subject	Data byte count	Default value	Setup value	Setting Details
System command	2	0	W		1	-	130	Initialization of setting value
							131	Stops IO-Link communication after reverting setting values to default values (Back-to-Box)
Device lock	12	0	R/W	✓	2	0	0	Unlocks the storage function.
							2	Storage function lock.
Tag name	24	0	R/W	✓	32	- [*]		Can be used to set a name for this unit, such as the device function or installation location.
Type of analog input	74	1 to 4	R/W	✓	4	0		Switches the input type for channels 0 to 3. The first byte is the value of channel 0. See the following for the meaning of each byte value: The input type is switched using process output data.
							0	Sets to 0 to 10 V voltage input.
							1	Sets to 0 to 10 V voltage input.
							2	Sets to -10 to 10 V voltage input.
							3	Sets to 0 to 5 V voltage input.
							4	Sets to 1 to 5 V voltage input.
							5	Sets to 0 to 20 mA current input.
Maximum span value	76	0	R/W	✓	8	32000		Sets the maximum span value for channels 0 to 3. Specifies the value given to the process input data when inputting the maximum value of the input range. The first two bytes are the value for channel 0.
							-32768 to 32767	Each channel is set separately. Subindex number 1 corresponds to channel 0.
Minimum span value	77	0	R/W	✓	8	0		Sets the minimum span value for channels 0 to 3. Specifies the value given to the process input data when inputting the input range value 0. The first two bytes are the value for channel 0.
							-32768 to 32767	Each channel is set separately. Subindex number 1 corresponds to channel 0.
Shift value	78	0	R/W	✓	8	0		Sets the shift value for channels 0 to 3. The span is calculated by adding this shift value to the process input data. The first two bytes are the value of channel 0.
							-32768 to 32767	Each channel is set separately. Subindex number 1 corresponds to channel 0.
Averaging time	79	1 to 4	R/W	✓	1	5		Sets the averaging time for channels 0 to 3.
							0	750 µs
							1	1.5 ms
							2	3 ms
							3	6 ms
							4	12 ms
							5	24 ms
Internal temperature	161	0	R		2			Returns the temperature on the internal board. The unit is 0.1°C.
							-2739 to 10461	
Operating time	162	0	R		4		0 to 4294967295	Returns the internal operation time. The unit is 7.5 minutes.
Displayed decimal point position	193	0	R/W	✓	4	0		Specifies the decimal point position for the process input data displayed on the IO-Link master UR series. The first byte corresponds to channel 0.
		1 to 4		✓	1		0 to 10	Each channel is set separately. Subindex number 1 corresponds to channel 0.
Display unit character string	194	1 to 4	R/W	✓	6	None		Specifies the unit character string for the process input data displayed on the IO-Link master UR series.
Device identification request (Find me)	204	0	R/W		1	0		Normal status
							1	Flash the COM LED at 0.55 second intervals

^{*1} R: Read only, W: Write only, R/W: Read/Write

^{*2} The default value is 32^{***} (asterisk) characters

This device complies with part 15 of the FCC Rules.

Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

^{*}This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

• Support for the China RoHS directive

For details on the support for the China RoHS (the Administrative Measure on the Control of Pollution Caused by Electronic Information Products), see the following website.
https://www.optex-fa.com/rohs_cn/

OPTEX FA CO., LTD.

[Headquarters]

91 Chudogi-awata-cho, Shimogyo-ku, Kyoto 600-8815 JAPAN

TEL +81-75-325-1314 FAX +81-75-325-2936

<https://www.optex-fa.com>

Ramco Innovations

www.optex-ramco.com

(800) 280-6933