

GX-F/H SERIES

Related Information

- General terms and conditions..... F-7
- Sensor selection guide P.803~
- Glossary of terms..... P.1482~
- General precautions P.1485~


panasonic.net/id/pidsx/global


For technical and application support contact Ramco Innovations today!


Email us at nsales@ramcoi.com

**Industry No. 1* in stable sensing**

* Based on research conducted by Panasonic Industrial Devices SUNX as of November 2012 among equivalent rectangular inductive sensors.

Can be installed with ample space

This sensor has the longest stable sensing range among the same level of rectangular inductive proximity sensors in the industry. It is easy to install the sensor.



Type	Maximum operation distance	Stable sensing range	
		GX-F/H series	Previous model
GX-□6	1.6 mm 0.063 in	0 to 1.3 mm 0.051 in	0 to 1.2 mm 0.047 in
GX-□8	2.5 mm 0.098 in	0 to 2.1 mm 0.083 in	0 to 1.8 mm 0.709 in
GX-□12	4.0 mm 0.157 in	0 to 3.3 mm 0.130 in	0 to 3.0 mm 0.118 in
GX-□15	5.0 mm 0.197 in	0 to 4.2 mm 0.165 in	0 to 4.0 mm 0.157 in
Long sensing range	8.0 mm 0.315 in	0 to 6.7 mm 0.264 in	0 to 6.4 mm 0.252 in


* With standard sensing object

Variation at the maximum operation distance is within ±8 %


Thorough adjustment and control of sensing sensitivity greatly reduces individual sensor differences and variations.

The work of adjusting sensor positions when using multiple sensors and when sensors have been replaced is much easier.



Example: GX-□8

**Temperature characteristics vary within ±8 %**

Components such as the sensor coil and core and product design have been totally revised to provide excellent temperature characteristics. Stable sensing can be obtained regardless of the time of day or the yearly season.




* Typical

APPLICATIONS**Muting control of light curtains****Positioning processing equipment****Positioning metal pallets****ENVIRONMENTAL RESISTANCE****10 times the durability! (Compared to previous models)**


The new integrated construction method used provides shock resistance of 10,000 m/s² (approx. 1,000 G in X, Y and Z directions for three times each), and vibration resistance clears durability tests of between 10 and 500 Hz (3 mm 0.118 in amplitude in X, Y and Z directions for 2 hours each). In addition, resistance to impulse noise is approx. three times greater than for previous models.

Checking up / down
operation of
compact molding
equipment



Shock resistance:
1,000 G

Sensing presence of metallic
objects on a part feeder



Vibration resistance: 500 Hz

**Highly resistant to water or oil!
IP68G* protective construction**

The new integrated construction method used improves environmental resistance performance. The IP68G prevents damage to the sensor by stopping water and oil getting inside.

* For details, refer to the "SPECIFICATIONS (p.812~)".

**FUNCTIONS****Indicators are easy to see over a wide field of view**

A prism with a wide field of view has been developed. This has greatly improved the visibility of the operation indicators.

GX-H□



GX-F□

**MOUNTING****Tightening strength increased with no damage! (excluding GX-□6)**

A metal sleeve has been inserted. It prevents the sensor from being damaged by tightening too much.

GX-□8, GX-□12



Approx. 1.4 times
greater than before

M3 screw
Tightening torque: 0.7 N · m or less

GX-□15



M3 screw
Tightening torque: 1 N · m or less

Conductor thickness doubled to make wiring much easier! (GX-□6/□8 only)

The conductor's thickness was doubled for the GX-□6/□8. This makes it easier to handle and perform crimping work on the cables. In addition, the tensile strength of the crimping area has become higher.

0.08 mm²
Previous model



0.15 mm²
GX-□6, GX-□8



Conductor thickness approx.
2 times greater

FIBER
SENSORS

LASER
SENSORS

PHOTOELECTRIC
SENSORS

MICRO
PHOTOELECTRIC
SENSORS

AREA
SENSORS

LIGHT CURTAINS /
SAFETY
COMPONENTS

PRESSURE /
FLOW
SENSORS

INDUCTIVE
PROXIMITY
SENSORS

PARTICULAR
USE SENSORS

SENSOR
OPTIONS

SIMPLE
WIRE-SAVING
UNITS

WIRE-SAVING
SYSTEMS

MEASUREMENT
SENSORS

STATIC ELECTRICITY
PREVENTION
DEVICES

LASER
MARKERS

PLC

HUMAN MACHINE
INTERFACES

ENERGY CONSUMPTION
VISUALIZATION
COMPONENTS

FA COMPONENTS

MACHINE VISION
SYSTEMS

UV CURING
SYSTEMS

Selection
Guide

Amplifier
Built-in
Amplifier-
separated

GX-F/H

GXL




GL

GX-M

**GX-U/GX-FU/
GX-N**

GX






ORDER GUIDE**GX-6 type**

Type		Appearance (mm in)	Sensing range (Note 1)	Model No. (Note 2)	Output	Output operation
NPN output	Front sensing		 <p>Maximum operation distance</p> <p>1.6 mm 0.063 in</p> <p>(0 to 1.3 mm 0 to 0.051 in)</p> <p>Stable sensing range</p>	GX-F6A	NPN open-collector transistor	Normally open
	Top sensing	GX-F6AI		Normally closed		
		GX-F6B		Normally open		
		GX-F6BI		Normally closed		
		GX-H6A		Normally open		
		GX-H6AI		Normally closed		
		GX-H6B		Normally open		
		GX-H6BI		Normally closed		
PNP output	Front sensing			GX-F6A-P	PNP open-collector transistor	Normally open
	Top sensing	GX-F6AI-P		Normally closed		
		GX-F6B-P		Normally open		
		GX-F6BI-P		Normally closed		
		GX-H6A-P		Normally open		
		GX-H6AI-P		Normally closed		
		GX-H6B-P		Normally open		
		GX-H6BI-P		Normally closed		

Notes: 1) The maximum operation distance stands for the maximum distance for which the sensor can detect the standard sensing object. The stable sensing range stands for the sensing range for which the sensor can stably detect the standard sensing object even if there is an ambient temperature drift and/or supply voltage fluctuation.

2) "I" in the model No. indicates a different frequency type.






GX-8 type

Type		Appearance (mm in)	Sensing range (Note 1)	Model No. (Note 2)	Output	Output operation	
NPN output	Front sensing		 <p>Maximum operation distance 2.5 mm 0.098 in</p> <p>(0 to 2.1 mm 0 to 0.083 in)</p> <p>Stable sensing range</p>	GX-F8A	NPN open-collector transistor	Normally open	
	Top sensing			GX-F8AI		Normally closed	
				GX-F8B		Normally open	
				GX-F8BI			
				GX-H8A			Normally open
				GX-H8AI		Normally closed	
				GX-H8B			
				GX-H8BI			
PNP output	Front sensing			GX-F8A-P	PNP open-collector transistor	Normally open	
	Top sensing			GX-F8AI-P		Normally closed	
				GX-F8B-P		Normally open	
				GX-F8BI-P			
				GX-H8A-P			Normally open
				GX-H8AI-P		Normally closed	
				GX-H8B-P			
				GX-H8BI-P			

Notes: 1) The maximum operation distance stands for the maximum distance for which the sensor can detect the standard sensing object. The stable sensing range stands for the sensing range for which the sensor can stably detect the standard sensing object even if there is an ambient temperature drift and/or supply voltage fluctuation.

2) "I" in the model No. indicates a different frequency type.

ORDER GUIDE**GX-12 type**

Type		Appearance (mm in)	Sensing range (Note 1)	Model No. (Note 2)	Output	Output operation	
NPN output	Front sensing			GX-F12A	NPN open-collector transistor	Normally open	
		GX-F12AI					
		GX-F12B		Normally closed			
		GX-F12BI					
		GX-H12A		Normally open			
		GX-H12BI		Normally closed			
	Top sensing			GX-H12A			
				GX-H12AI			
				GX-H12B			
PNP output	Front sensing				GX-F12A-P	PNP open-collector transistor	Normally open
		GX-F12AI-P					
		GX-F12B-P			Normally closed		
		GX-F12BI-P					
		GX-H12A-P	Normally open				
		GX-H12AI-P					
		GX-H12B-P					
		GX-H12BI-P	Normally closed				

Notes: 1) The maximum operation distance stands for the maximum distance for which the sensor can detect the standard sensing object.

The stable sensing range stands for the sensing range for which the sensor can stably detect the standard sensing object even if there is an ambient temperature drift and/or supply voltage fluctuation.

2) "I" in the model No. indicates a different frequency type.

GX-15 type

Type		Appearance (mm in)	Sensing range (Note 1)	Model No. (Note 2)	Output	Output operation	
NPN output	Front sensing			GX-F15A	NPN open-collector transistor	Normally open	
	Top sensing	GX-F15AI		Normally closed			
		GX-F15B				Normally open	
		GX-F15BI					Normally closed
		GX-H15A					
		GX-H15AI				Normally closed	
GX-H15B	Normally open						
GX-H15BI		Normally closed					
PNP output	Front sensing				GX-F15A-P	PNP open-collector transistor	Normally open
	Top sensing	GX-F15AI-P		Normally closed			
		GX-F15B-P			Normally open		
		GX-F15BI-P					Normally closed
		GX-H15A-P	Normally open				
		GX-H15AI-P			Normally closed		
GX-H15B-P	Normally open						
GX-H15BI-P		Normally closed					

Notes: 1) The maximum operation distance stands for the maximum distance for which the sensor can detect the standard sensing object.

The stable sensing range stands for the sensing range for which the sensor can stably detect the standard sensing object even if there is an ambient temperature drift and/or supply voltage fluctuation.

2) "I" in the model No. indicates a different frequency type.

FIBER SENSORS

LASER SENSORS

PHOTO-ELECTRIC SENSORS

MICRO PHOTO-ELECTRIC SENSORS

AREA SENSORS

LIGHT CURTAINS / SAFETY COMPONENTS

PRESSURE / FLOW SENSORS

INDUCTIVE PROXIMITY SENSORS

PARTICULAR USE SENSORS

SENSOR OPTIONS

SIMPLE WIRE-SAVING UNITS

WIRE-SAVING SYSTEMS

MEASUREMENT SENSORS

STATIC ELECTRICITY PREVENTION DEVICES

LASER MARKERS

PLC

HUMAN MACHINE INTERFACES

ENERGY CONSUMPTION VISUALIZATION COMPONENTS

FA COMPONENTS

MACHINE VISION SYSTEMS

UV CURING SYSTEMS

Selection Guide

Amplifier Built-in

Amplifier-separated

GX-F/H

GXL

GL

GX-M

GX-U/GX-FU/GX-N

GX

ORDER GUIDE**GX-15 (Long sensing range) type**

Type		Appearance (mm in)	Sensing range (Note 1)	Model No. (Note 2)	Output	Output operation
NPN output	Front sensing		<p>Maximum operation distance 8.0 mm 0.315 in</p> <p>(0 to 6.7 mm 0 to 0.264 in)</p> <p>Stable sensing range</p>	GX-FL15A	NPN open-collector transistor	Normally open
	Top sensing			GX-FL15AI		Normally closed
				GX-FL15B		Normally open
				GX-FL15BI		Normally closed
				GX-HL15A		Normally open
				GX-HL15AI		Normally closed
				GX-HL15B		Normally open
	PNP output	Front sensing				GX-FL15A-P
Top sensing			GX-FL15AI-P	Normally closed		
			GX-FL15B-P	Normally open		
			GX-FL15BI-P	Normally closed		
			GX-HL15A-P	Normally open		
			GX-HL15AI-P	Normally closed		
			GX-HL15B-P	Normally open		
Top sensing			GX-HL15BI-P	Normally closed		



Notes: 1) The maximum operation distance stands for the maximum distance for which the sensor can detect the standard sensing object. The stable sensing range stands for the sensing range for which the sensor can stably detect the standard sensing object even if there is an ambient temperature drift and/or supply voltage fluctuation.
2) "I" in the model No. indicates a different frequency type.

5 m 16.404 ft cable length type, flexible cable type



5 m 16.404 ft cable length type (standard: 1 m 3.281 ft) and flexible cable (excluding 5 m 16.404 ft cable length type) are available. However, long sensing range type is not available. When ordering 5 m 16.404 ft cable length type, suffix "-C5" to the model No. When ordering flexible cable type, suffix "-R" to the model No.
(e.g.) 5 m 16.404 ft cable length type of **GX-F15AI-P** is "**GX-F15AI-P-C5**". Flexible cable type of **GX-F15AI-P** is "**GX-F15AI-P-R**".

OPTIONS

Designation	Model No.	Description
Sensor mounting bracket	MS-GX6-1	Mounting bracket for GX-6 type (recommended). Sensors can be mounted closely together for space-saving.
	MS-GL6-1	Mounting brackets for GX-6 type Sensor mounting brackets for GL-6 can be used. Interchange is possible.
	MS-GL6-2	
	MS-GXL8-4	Mounting bracket for GX-8 type
	MS-GXL15	Mounting bracket for GX-15 type
Aluminum sheet	MS-A15F	For GX-FL15□(-P)
	MS-A15H	For GX-HL15□(-P)
Mounting sleeve	MS-GX8-1×10 10 pcs. per set	Mounting sleeve for GX-8 type Screw, nut, bracket of GXL-8 series can be used by inserting the bracket into the mounting hole of GX-8 type when replacing 3-wire type GXL-8 series (discontinued model) with GX-8 type.

Sensor mounting bracket• **MS-GX6-1**• **MS-GL6-1**• **MS-GL6-2**• **MS-GXL8-4****Aluminum sheet**

- **MS-A15F**
- **MS-A15H**

• **MS-GXL15**

SPECIFICATIONS**GX-6 type**

		Type	NPN output		PNP output	
		Front sensing	GX-F6A(I)	GX-F6B(I)	GX-F6A(I)-P	GX-F6B(I)-P
Item	Model No. (Note 2)	Top sensing	GX-H6A(I)	GX-H6B(I)	GX-H6A(I)-P	GX-H6B(I)-P
Max. operation distance (Note 3)			1.6 mm 0.063 in ± 8 %			
Stable sensing range (Note 3)			0 to 1.3 mm 0 to 0.051 in			
Standard sensing object			Iron sheet 12 × 12 × t 1 mm 0.472 × 0.472 × t 0.039 in			
Hysteresis			20 % or less of operation distance (with standard sensing object)			
Repeatability			Along sensing axis, perpendicular to sensing axis: 0.04 mm 0.0016 in or less			
Supply voltage			12 to 24 V DC ⁺¹⁰ ₋₁₅ % Ripple P-P 10 % or less			
Current consumption			15 mA or less			
Output		NPN open-collector transistor <ul style="list-style-type: none">Maximum sink current: 100 mAApplied voltage: 30 V DC or less (between output and 0 V)Residual voltage: 2 V or less (at 100 mA sink current)			PNP open-collector transistor <ul style="list-style-type: none">Maximum source current: 100 mAApplied voltage: 30 V DC or less (between output and +V)Residual voltage: 2 V or less (at 100 mA source current)	
		Utilization category	DC-12 or DC-13			
		Output operation	Normally closed	Normally closed	Normally closed	Normally closed
Max. response frequency			400 Hz			
Operation indicator			Orange LED (lights up when the output is ON)			
Environmental resistance	Pollution degree	3 (Industrial environment)				
	Protection	IP68 (IEC), IP68G (Note 4, 5)				
	Ambient temperature	−25 to +70 °C −13 to +158 °F, Storage: −40 to +85 °C −40 to +185 °F				
	Ambient humidity	35 to 85 % RH, Storage: 35 to 95 % RH				
	EMC	EN 60947-5-2				
	Voltage withstandability	1,000 V AC for one min. between all supply terminals connected together and enclosure				
	Insulation resistance	50 MΩ, or more, with 500 V DC megger between all supply terminals connected together and enclosure				
	Vibration resistance	10 to 500 Hz frequency, 3 mm 0.118 in amplitude (Max. 20 G) in X, Y and Z directions for two hours each				
	Shock resistance	10,000 m/s ² acceleration (1,000 G approx.) in X, Y and Z directions for three times each				
Sensing range variation	Temperature characteristics	Over ambient temperature range −25 to +70 °C −13 to +158 °F: Within ± 8 % of sensing range at +23 °C +73 °F				
	Voltage characteristics	Within ±2 % for ⁺¹⁰ ₋₁₅ % fluctuation of the supply voltage				
Material			Enclosure: PBT, Indicator part: Polyester			
Cable			0.15 mm ² 3-core oil, heat and cold resistant cabtyre cable, 1 m 3.281 ft long			
Cable extension			Extension up to total 100 m 328.084 ft is possible with 0.3 mm ² , or more, cable.			
Net weight			15 g approx.			

Notes: 1) Where measurement conditions have not been specified precisely, the conditions used were an ambient temperature of +23 °C **+73 °F**.

2) "I" in the model No. indicates a different frequency type.

3) The maximum operation distance stands for the maximum distance for which the sensor can detect the standard sensing object.

The stable sensing range stands for the sensing range for which the sensor can stably detect the standard sensing object even if there is an ambient temperature drift and/or supply voltage fluctuation.

4) Panasonic Industrial Devices SUNX's IP68 test method

① Immerse at 0 m below 0 °C **+32 °F** water surface and leave for 30 min. Then, immerse at 0 m below +70 °C **+158 °F** water surface and leave for 30 min.

② Regard the heat shock test in ① as one cycle and perform 20 cycles.

③ Leave in water at a depth of 1 m **3.281 ft** in water for 500 hours.

④ After tests ① to ③, insulation resistance, voltage withstandability, current consumption, and sensing range must meet the standard values.

5) If using the sensor in an environment where cutting oil droplets splatter, the sensor may be deteriorated due to added substances in the oil.

Please check the resistivity of the sensor against the cutting oil you are using beforehand.

FIBER
SENSORSLASER
SENSORSPHOTO-
ELECTRIC
SENSORSMICRO
PHOTO-
ELECTRIC
SENSORSAREA
SENSORSLIGHT
CURTAINS/
SAFETY
COMPONENTSPRESSURE/
FLOW
SENSORSINDUCTIVE
PROXIMITY
SENSORSPARTICULAR
USE
SENSORSSENSOR
OPTIONSSIMPLE
WIRE-
SAVING
UNITSWIRE-
SAVING
SYSTEMSMEASURE-
MENT
SENSORSSTATIC
ELECTRICITY
PREVENTION
DEVICESLASER
MARKERS

PLC

HUMAN
MACHINE
INTERFACESENERGY
CONSUMPTION
VISUALIZATION
COMPONENTSFA
COMPONENTSMACHINE
VISION
SYSTEMSUV
CURING
SYSTEMSSelection
GuideAmplifier
Built-inAmplifier-
separated**GX-F/H****GXL****GL****GX-M**GX-UGX-FH/
GX-N**GX**

SPECIFICATIONS

GX-8 type

Item	Model No. (Note 2)	Type	NPN output		PNP output	
		Front sensing	GX-F8A(I)	GX-F8B(I)	GX-F8A(I)-P	GX-F8B(I)-P
		Top sensing	GX-H8A(I)	GX-H8B(I)	GX-H8A(I)-P	GX-H8B(I)-P
Max. operation distance (Note 3)			2.5 mm 0.098 in ± 8 %			
Stable sensing range (Note 3)			0 to 2.1 mm 0 to 0.083 in			
Standard sensing object			Iron sheet 15 × 15 × t 1 mm 0.591 × 0.591 × t 0.039 in			
Hysteresis			20 % or less of operation distance (with standard sensing object)			
Repeatability			Along sensing axis, perpendicular to sensing axis: 0.04 mm 0.0016 in or less			
Supply voltage			12 to 24 V DC $\begin{smallmatrix} +10 \\ -15 \end{smallmatrix}$ % Ripple P-P 10 % or less			
Current consumption			15 mA or less			
Output		NPN open-collector transistor • Maximum sink current: 100 mA • Applied voltage: 30 V DC or less (between output and 0 V) • Residual voltage: 2 V or less (at 100 mA sink current)			PNP open-collector transistor • Maximum source current: 100 mA • Applied voltage: 30 V DC or less (between output and +V) • Residual voltage: 2 V or less (at 100 mA source current)	
		Utilization category	DC-12 or DC-13			
		Output operation	Normally open	Normally closed	Normally open	Normally closed
Max. response frequency			500 Hz			
Operation indicator			Orange LED (lights up when the output is ON)			
Environmental resistance	Pollution degree		3 (Industrial environment)			
	Protection		IP68 (IEC), IP68G (Note 4, 5)			
	Ambient temperature		−25 to +70 °C −13 to +158 °F , Storage: −40 to +85 °C −40 to +185 °F			
	Ambient humidity		35 to 85 % RH, Storage: 35 to 95 % RH			
	EMC		EN 60947-5-2			
	Voltage withstandability		1,000 V AC for one min. between all supply terminals connected together and enclosure			
	Insulation resistance		50 MΩ, or more, with 500 V DC megger between all supply terminals connected together and enclosure			
	Vibration resistance		10 to 500 Hz frequency, 3 mm 0.118 in amplitude (Max. 20 G) in X, Y and Z directions for two hours each			
	Shock resistance		10,000 m/s ² acceleration (1,000 G approx.) in X, Y and Z directions for three times each			
Sensing range variation	Temperature characteristics		Over ambient temperature range −25 to +70 °C −13 to +158 °F : Within ± 8 % of sensing range at +23 °C +73 °F			
	Voltage characteristics		Within ±2 % for $\begin{smallmatrix} +10 \\ -15 \end{smallmatrix}$ % fluctuation of the supply voltage			
Material			Enclosure: PBT, Indicator part: Polyester			
Cable			0.15 mm ² 3-core oil, heat and cold resistant cabtyre cable, 1 m 3.281 ft long			
Cable extension			Extension up to total 100 m 328.084 ft is possible with 0.3 mm ² , or more, cable.			
Net weight			Front sensing type: 15 g approx., Top sensing type: 20 g approx..			

Notes: 1) Where measurement conditions have not been specified precisely, the conditions used were an ambient temperature of +23 °C **+73 °F**.

2) "I" in the model No. indicates a different frequency type.

3) The maximum operation distance stands for the maximum distance for which the sensor can detect the standard sensing object.

The stable sensing range stands for the sensing range for which the sensor can stably detect the standard sensing object even if there is an ambient temperature drift and/or supply voltage fluctuation.

4) Panasonic Industrial Devices SUNX's IP68 test method

① Immerse at 0 m below 0 °C **+32 °F** water surface and leave for 30 min. Then, immerse at 0 m below +70 °C **+158 °F** water surface and leave for 30 min.

② Regard the heat shock test in ① as one cycle and perform 20 cycles.

③ Leave in water at a depth of 1 m **3.281 ft** in water for 500 hours.

④ After tests ① to ③, insulation resistance, voltage withstandability, current consumption, and sensing ranges must meet the standard values.

5) If using the sensor in an environment where cutting oil droplets splatter, the sensor may deteriorate due to added substances in the oil.

Please check the resistivity of the sensor against the cutting oil you are using beforehand.

GX-F/H

GXL

GL

GX-M

GX-UGX-FU/

GX-N

GX

SPECIFICATIONS**GX-12 type**

Item	Model No. (Note 2)	Type	NPN output		PNP output	
		Front sensing	GX-F12A(I)	GX-F12B(I)	GX-F12A(I)-P	GX-F12B(I)-P
Top sensing			GX-H12A(I)	GX-H12B(I)	GX-H12A(I)-P	GX-H12B(I)-P
Max. operation distance (Note 3)			4.0 mm 0.157 in ± 8 %			
Stable sensing range (Note 3)			0 to 3.3 mm 0 to 0.130 in			
Standard sensing object			Iron sheet 20 × 20 × t 1 mm 0.787 × 0.787 × t 0.039 in			
Hysteresis			20 % or less of operation distance (with standard sensing object)			
Repeatability			Along sensing axis, perpendicular to sensing axis: 0.04 mm 0.0016 in or less			
Supply voltage			12 to 24 V DC $\begin{smallmatrix} +10 \\ -15 \end{smallmatrix}$ % Ripple P-P 10 % or less			
Current consumption			15 mA or less			
Output			NPN open-collector transistor		PNP open-collector transistor	
			• Maximum sink current: 100 mA • Applied voltage: 30 V DC or less (between output and 0 V) • Residual voltage: 2 V or less (at 100 mA sink current)		• Maximum source current: 100 mA • Applied voltage: 30 V DC or less (between output and +V) • Residual voltage: 2 V or less (at 100 mA source current)	
			Utilization category		DC-12 or DC-13	
Output operation			Normally open	Normally closed	Normally open	Normally closed
Max. response frequency			500 Hz			
Operation indicator			Orange LED (lights up when the output is ON)			
Environmental resistance	Pollution degree		3 (Industrial environment)			
	Protection		IP68 (IEC), IP68G (Note 4, 5)			
	Ambient temperature		−25 to +70 °C −13 to +158 °F , Storage: −40 to +85 °C −40 to +185 °F			
	Ambient humidity		35 to 85 % RH, Storage: 35 to 95 % RH			
	EMC		EN 60947-5-2			
	Voltage withstandability		1,000 V AC for one min. between all supply terminals connected together and enclosure			
	Insulation resistance		50 MΩ, or more, with 500 V DC megger between all supply terminals connected together and enclosure			
	Vibration resistance		10 to 500 Hz frequency, 3 mm 0.118 in amplitude (Max. 20 G) in X, Y and Z directions for two hours each			
Shock resistance			10,000 m/s ² acceleration (1,000 G approx.) in X, Y and Z directions for three times each			
Sensing range variation	Temperature characteristics		Over ambient temperature range −25 to +70 °C −13 to +158 °F : Within ±8 % of sensing range at +23 °C +73 °F			
	Voltage characteristics		Within ±2 % for $\begin{smallmatrix} +10 \\ -15 \end{smallmatrix}$ % fluctuation of the supply voltage			
Material			Enclosure: PBT, Indicator part: Polyester			
Cable			0.15 mm ² 3-core oil, heat and cold resistant cabtyre cable, 1 m 3.281 ft long			
Cable extension			Extension up to total 100 m 328.084 ft is possible with 0.3 mm ² , or more, cable.			
Net weight			Front sensing type: 20 g approx., Top sensing type: 20 g approx..			

Notes: 1) Where measurement conditions have not been specified precisely, the conditions used were an ambient temperature of +23 °C **+73 °F**.

2) "I" in the model No. indicates a different frequency type.

3) The maximum operation distance stands for the maximum distance for which the sensor can detect the standard sensing object.

The stable sensing range stands for the sensing range for which the sensor can stably detect the standard sensing object even if there is an ambient temperature drift and/or supply voltage fluctuation.

4) Panasonic Industrial Devices SUNX's IP68 test method

① Immerse at 0 m below 0 °C **+32 °F** water surface and leave for 30 min. Then, immerse at 0 m below +70 °C **+158 °F** water surface and leave for 30 min.

② Regard the heat shock test in ① as one cycle and perform 20 cycles.

③ Leave in water at a depth of 1 m **3.281 ft** in water for 500 hours.

④ After tests ① to ③, insulation resistance, voltage withstandability, current consumption, and sensing ranges must meet the standard values.

5) If using the sensor in an environment where cutting oil droplets splatter, the sensor may deteriorate due to added substances in the oil.

Please check the resistivity of the sensor against the cutting oil you are using beforehand.

FIBER SENSORS

LASER SENSORS

PHOTO-ELECTRIC SENSORS

MICRO PHOTO-ELECTRIC SENSORS

AREA SENSORS

LIGHT CURTAINS / SAFETY COMPONENTS

PRESSURE / FLOW SENSORS

INDUCTIVE PROXIMITY SENSORS

PARTICULAR USE SENSORS

SENSOR OPTIONS

SIMPLE WIRE-SAVING UNITS

WIRE-SAVING SYSTEMS

MEASURE-MENT SENSORS

STATIC ELECTRICITY PREVENTION DEVICES

LASER MARKERS

PLC

HUMAN MACHINE INTERFACES

ENERGY CONSUMPTION VISUALIZATION COMPONENTS

FA COMPONENTS

MACHINE VISION SYSTEMS

UV CURING SYSTEMS

Selection Guide

Amplifier Built-in

Amplifier-separated

GX-F/H**GXL****GL****GX-M**

GX-U/GX-FU/

GX-N

GX

SPECIFICATIONS**GX-15 type**

Item	Model No. (Note 2)	Type	NPN output				PNP output				
					Long sensing range				Long sensing range		
			Front sensing	GX-F15A(I)	GX-F15B(I)	GX-FL15A(I)	GX-FL15B(I)	GX-F15A(I)-P	GX-F15B(I)-P	GX-FL15A(I)-P	GX-FL15B(I)-P
		Top sensing	GX-H15A(I)	GX-H15B(I)	GX-HL15A(I)	GX-HL15B(I)	GX-H15A(I)-P	GX-H15B(I)-P	GX-HL15A(I)-P	GX-HL15B(I)-P	
Max. operation distance (Note 3)			5.0 mm 0.197 in ± 8 %		8.0 mm 0.315 in ± 8 % (Note 4)		5.0 mm 0.197 in ± 8 %		8.0 mm 0.315 in ± 8 % (Note 4)		
Stable sensing range (Note 3)			0 to 4.2 mm 0 to 0.165 in		0 to 6.7 mm 0 to 0.264 in (Note 4)		0 to 4.2 mm 0 to 0.165 in		0 to 6.7 mm 0 to 0.264 in (Note 4)		
Standard sensing object			Iron sheet 20 × 20 × t 1 mm 0.7874 × 0.7874 × t 0.039 in		Iron sheet 30 × 30 × t 1 mm 1.181 × 1.181 × t 0.039 in		Iron sheet 20 × 20 × t 1 mm 0.7874 × 0.7874 × t 0.039 in		Iron sheet 30 × 30 × t 1 mm 1.181 × 1.181 × t 0.039 in		
Hysteresis			20 % or less of operation distance (with standard sensing object)								
Repeatability			Along sensing axis, perpendicular to sensing axis: 0.04 mm 0.0016 in or less								
Supply voltage			12 to 24 V DC ⁺¹⁰ ₋₁₅ % Ripple P-P 10 % or less								
Current consumption			15 mA or less								
Output			NPN open-collector transistor • Maximum sink current: 100 mA • Applied voltage: 30 V DC or less (between output and 0 V) • Residual voltage: 2 V or less (at 100 mA sink current)				PNP open-collector transistor • Maximum source current: 100 mA • Applied voltage: 30 V DC or less (between output and +V) • Residual voltage: 2 V or less (at 100 mA source current)				
			Utilization category			DC-12 or DC-13					
			Output operation			Normally open	Normally closed	Normally open	Normally closed	Normally open	Normally closed
Max. response frequency			250 Hz		150 Hz (Note 5)		250 Hz		150 Hz (Note 5)		
Operation indicator			Orange LED (lights up when the output is ON)								
Environmental resistance	Pollution degree		3 (Industrial environment)								
	Protection		IP68 (IEC), IP68G (Note 6, 7)								
	Ambient temperature		-25 to +70 °C -13 to +158 °F, Storage: -40 to +85 °C -40 to +185 °F								
	Ambient humidity		35 to 85 % RH, Storage: 35 to 95 % RH								
	EMC		EN 60947-5-2								
	Voltage withstandability		1,000 V AC for one min. between all supply terminals connected together and enclosure								
	Insulation resistance		50 MΩ, or more, with 500 V DC megger between all supply terminals connected together and enclosure								
	Vibration resistance		10 to 500 Hz frequency, 3 mm 0.118 in amplitude (Max. 20 G) in X, Y and Z directions for two hours each								
	Shock resistance		10,000 m/s ² acceleration (1,000 G approx.) in X, Y and Z directions for three times each								
Sensing range variation	Temperature characteristics		Over ambient temperature range -25 to +70 °C -13 to +158 °F: Within ± 8 % of sensing range at +23 °C +73 °F								
	Voltage characteristics		Within ±2 % for ⁺¹⁰ ₋₁₅ % fluctuation of the supply voltage								
Material			Enclosure: PBT, Indicator part: Polyester								
Cable			0.15 mm ² 3-core oil, heat and cold resistant cabtyre cable, 1 m 3.281 ft long								
Cable extension			Extension up to total 100 m 328.084 ft is possible with 0.3 mm ² , or more, cable.								
Net weight			20 g approx.								

Notes: 1) Where measurement conditions have not been specified precisely, the conditions used were an ambient temperature of +23 °C **+73 °F**.

2) "I" in the model No. indicates a different frequency type.

3) The maximum operation distance stands for the maximum distance for which the sensor can detect the standard sensing object.

The stable sensing range stands for the sensing range for which the sensor can stably detect the standard sensing object even if there is an ambient temperature drift and/or supply voltage fluctuation.

4) This is the numerical value which the sensor mount onto an insulant plate. When mounted onto a steel or stainless steel plate, insert the optional aluminum sheet between the sensor and the plate.

5) This is the numerical value which the sensor mount onto an insulant plate. When mounted onto a metallic plate, max. response frequency will decrease.

6) Panasonic Industrial Devices SUNX's IP68 test method

① Immerse at 0 m below 0 °C **+32 °F** water surface and leave for 30 min. Then, immerse at 0 m below +70 °C **+158 °F** water surface and leave for 30 min.

② Regard the heat shock test in ① as one cycle and perform 20 cycles.

③ Leave in water at a depth of 1 m **3.281 ft** in water for 500 hours.

④ After tests ① to ③, insulation resistance, voltage withstandability, current consumption, and sensing range must meet the standard values.

7) If using the sensor in an environment where cutting oil droplets splatter, the sensor may be deteriorated due to added substances in the oil.

Please check the resistivity of the sensor against the cutting oil you are using beforehand.

GX-F/H

GXL


GL

GX-M

GX-UGX-FU/



GX-N

GX

I/O CIRCUIT DIAGRAMS**NPN output type****I/O circuit diagram**


Symbols ... D1: Reverse supply polarity protection diode
D2: Reverse output polarity protection diode
Zd: Surge absorption zener diode
Tr : NPN output transistor

Note: The output does not incorporate a short-circuit protection circuit.
Do not connect it directly to a power supply or a capacitive load.

Wiring diagram**PNP output type****I/O circuit diagram**



Symbols ... D1: Reverse supply polarity protection diode
D2: Reverse output polarity protection diode
Zd: Surge absorption zener diode
Tr : PNP output transistor

Note: The output does not incorporate a short-circuit protection circuit.
Do not connect it directly to a power supply or a capacitive load.



Wiring diagramFIBER
SENSORSLASER
SENSORSPHOTO-
ELECTRIC
SENSORSMICRO
PHOTO-
ELECTRIC
SENSORSAREA
SENSORSLIGHT
CURTAINS/
SAFETY
COMPONENTSPRESSURE/
FLOW
SENSORS**INDUCTIVE
PROXIMITY
SENSORS**PARTICULAR
USE
SENSORSSENSOR
OPTIONSSIMPLE
WIRE-
SAVING
UNITSWIRE-
SAVING
SYSTEMSMEASURE-
MENT
SENSORSSTATIC
ELECTRICITY
PREVENTION
DEVICESLASER
MARKERS

PLC



HUMAN
MACHINE
INTERFACESENERGY
CONSUMPTION
VISUALIZATION
COMPONENTSFA
COMPONENTSMACHINE
VISION
SYSTEMSUV
CURING
SYSTEMSSelection
GuideAmplifier
Built-inAmplifier-
separated**GX-F/H****GXL****GL****GX-M**GX-U/GX-FU/
GX-N**GX**

SENSING CHARACTERISTICS (TYPICAL)**GX-6 type****Sensing field****Correlation between sensing object size and sensing range**



As the sensing object size becomes smaller than the standard size (iron sheet $12 \times 12 \times 1$ mm $0.472 \times 0.472 \times 0.039$ in), the sensing range shortens as shown in the left figure.

GX-8 type**Sensing field****Correlation between sensing object size and sensing range**



As the sensing object size becomes smaller than the standard size (iron sheet $15 \times 15 \times 1$ mm $0.591 \times 0.591 \times 0.039$ in), the sensing range shortens as shown in the left figure.

GX-12 type**Sensing field****Correlation between sensing object size and sensing range**

As the sensing object size becomes smaller than the standard size (iron sheet $20 \times 20 \times 1$ mm $0.787 \times 0.787 \times 0.039$ in), the sensing range shortens as shown in the left figure.

GX-15 type**Sensing field****Correlation between sensing object size and sensing range**

As the sensing object size becomes smaller than the standard size (iron sheet $20 \times 20 \times 1$ mm $0.787 \times 0.787 \times 0.039$ in), the sensing range shortens as shown in the left figure.

SENSING CHARACTERISTICS (TYPICAL)**GX-15 (Long sensing range) type****Sensing field****Correlation between sensing object size and sensing range**

As the sensing object size becomes smaller than the standard size (iron sheet 30 × 30 × t 1 mm 1.181 × 1.181 × t 0.039 in), the sensing range shortens as shown in the left figure.

PRECAUTIONS FOR PROPER USE

Refer to p.1485~ for general precautions.



- Never use this product as a sensing device for personnel protection.
- In case of using sensing devices for personnel protection, use products which meet laws and standards, such as OSHA, ANSI or IEC etc., for personnel protection applicable in each region or country.


Mounting**GX-6 type**

- Use the optional sensor mounting bracket when installing.


<When using MS-GX6-1 (recommended)>

- To mount the sensor with a nut, the mounting hole diameter should be $\phi 3.4$ mm $\phi 0.134$ in.


- ① Insert the sensor into the bracket as shown on the right.
- ② Push the sensor until the bracket hook is lodged in the groove on the upper portion of the sensor.
- ③ Fix the bracket in place with M3 pan head screw.

**<When using MS-GL6-1 / MS-GL6-2>**


- To mount the sensor with a nut, the mounting hole diameter should be $\phi 3.4$ mm $\phi 0.134$ in.

**GX-8 type**


- Make sure to use a M3 (length: 12 mm 0.472 in or more) truss head screw. The tightening torque should be 0.7 N·m or less. (Do not use a flat head screw or a pan head screw.)

**GX-12 type**


- The tightening torque should be 0.7 N·m or less.
- To mount the sensor with a nut, the mounting hole diameter should be $\phi 3.4$ mm $\phi 0.134$ in. Further, the hole in which the boss is inserted should be $\phi 2.5$ mm $\phi 0.098$ in and 3 mm $\phi 0.118$ in, or more, deep.

**GX-15 type**

- The tightening torque should be 1 N·m or less.
- To mount the sensor with a nut, the mounting hole diameter should be $\phi 3.4$ mm $\phi 0.134$ in.



- When installing the long sensing range type on iron or stainless steel plate, put the optional aluminum sheet in between the sensor and the plate.



FIBER SENSORS

LASER SENSORS

PHOTO-ELECTRIC SENSORS

MICRO PHOTO-ELECTRIC SENSORS

AREA SENSORS

LIGHT CURTAINS / SAFETY COMPONENTS

PRESSURE / FLOW SENSORS

INDUCTIVE PROXIMITY SENSORS

PARTICULAR USE SENSORS

SENSOR OPTIONS

SIMPLE WIRE-SAVING UNITS

WIRE-SAVING SYSTEMS

MEASUREMENT SENSORS

STATIC ELECTRICITY PREVENTION DEVICES

LASER MARKERS

PLC

HUMAN MACHINE INTERFACES

ENERGY CONSUMPTION VISUALIZATION COMPONENTS

FA COMPONENTS

MACHINE VISION SYSTEMS

UV CURING SYSTEMS

Selection Guide

Amplifier Built-in

Amplifier-separated

GX-F/H**GXL****GL****GX-M**

GX-UGX-F/H


GX

PRECAUTIONS FOR PROPER USE

Refer to p.1485~ for general precautions.


Influence of surrounding metal

- When there is a metal near the sensor, keep the minimum separation distance specified below.

Front sensing type

	GX-F6 type	GX-F8 type	GX-F12 type	GX-F15 type	GX-FL15 type
A	6 mm 0.236 in (Note 1)	7.4 mm 0.291 in	7.1 mm 0.280 in	8 mm 0.315 in	8 mm 0.315 in (Note 2)
B	8 mm 0.315 in	8 mm 0.315 in	20 mm 0.787 in	20 mm 0.787 in	30 mm 1.181 in
C	3 mm 0.118 in	3 mm 0.118 in	7 mm 0.276 in	7 mm 0.276 in	10 mm 0.394 in

- Notes: 1) When using **MS-GX6-1** (recommended mounting bracket), the distance "A" including the thickness of mounting bracket will be 6.4 mm **0.252 in**.
2) The **GX-FL15** type should be mounted on an insulator. To mount it on an iron or stainless steel, use the enclosed aluminum sheet.

Top sensing type

	GX-H6 type	GX-H8 type	GX-H12 type	GX-H15 type	GX-HL15 type
D	3 mm 0.118 in	4 mm 0.157 in	7 mm 0.276 in	6 mm 0.236 in	12 mm 0.472 in
E	10 mm 0.394 in	10 mm 0.394 in	20 mm 0.787 in	20 mm 0.787 in	30 mm 1.181 in
F	2 mm 0.079 in	3 mm 0.118 in	3 mm 0.118 in	0 mm 0 in	10 mm 0.394 in (Note)
G	2 mm 0.079 in	3 mm 0.118 in	3 mm 0.118 in	3 mm 0.118 in	10 mm 0.394 in



Note: When **GX-HL15** type is mounted on an insulator or seated on the enclosed aluminum sheet, the distance "F" can be zero.

Mutual interference prevention

- When two or more sensors are installed in parallel or face to face, keep the minimum separation distance specified below to avoid mutual interference.

		H	J
GX-F6	Between "I" type and non "I" type	0 mm (Note 2)	15 mm 0.591 in
GX-H6	Between two "I" types or two non "I" types	13 mm 0.512 in	25 mm 0.984 in
GX-F8	Between "I" type and non "I" type	0 mm (Note 2)	15 mm 0.591 in
GX-H8	Between two "I" types or two non "I" types	20 mm 0.787 in	35 mm 1.378 in
GX-F12	Between "I" type and non "I" type	0 mm (Note 2)	25 mm 0.984 in
GX-H12	Between two "I" types or two non "I" types	25 mm 0.984 in	50 mm 1.969 in
GX-F15	Between "I" type and non "I" type	0 mm (Note 2)	25 mm 0.984 in
GX-H15	Between two "I" types or two non "I" types	45 mm 1.772 in	70 mm 2.756 in
GX-FL15	Between "I" type and non "I" type	0 mm (Note 2)	25 mm 0.984 in
GX-HL15	Between two "I" types or two non "I" types	110 mm 3.059 in	170 mm 6.693 in

- Notes: 1) "I" in the model No. specifies the different frequency type.
2) Close mounting is possible for up to two sensors. When mounting three sensors or more at an equal spacing, align the model with "I" and the model without "I" alternately. The minimum value of dimension "H" should be as given below.
GX-F6 / H6 type: 3.5mm 0.138 in
GX-F8 / H8 type: 6mm 0.236 in
GX-F12 / H12 type: 6.5mm 0.256 in
GX-F15 / H15 type: 15mm 0.591 in
GX-FL15 / HL15 type: 47.5mm 1.870 in

Front sensing**Top sensing****Sensing range**

- The sensing range is specified for the standard sensing object. With a non-ferrous metal, the sensing range is obtained by multiplying with the correction coefficient specified below. Further, the sensing range also changes if the sensing object is smaller than the standard sensing object or if the sensing object is plated.

Correction coefficient

Model No.	GX-F6 GX-H6 type	GX-F8 GX-H8 type	GX-F12 GX-H12 type	GX-F15 GX-H15 type	GX-FL15 type	GX-HL15 type
Metal						
Iron	1	1	1	1	1	1
Stainless steel (SUS304)	0.76 approx.	0.76 approx.	0.79 approx.	0.68 approx.	0.70 approx.	0.76 approx.
Brass	0.50 approx.	0.50 approx.	0.56 approx.	0.47 approx.	0.45 approx.	0.50 approx.
Aluminum	0.48 approx.	0.48 approx.	0.53 approx.	0.45 approx.	0.43 approx.	0.48 approx.

Wiring

- The output does not incorporate a short-circuit protection circuit. Do not connect it directly to a power supply or a capacitive load.

Others

- Do not use during the initial transient time (50 ms) after the power supply is switched on.





FIBER
SENSORSLASER
SENSORSPHOTO-
ELECTRIC
SENSORSMICRO
PHOTO-
ELECTRIC
SENSORSAREA
SENSORSLIGHT
CURTAINS/
SAFETY
COMPONENTSPRESSURE/
FLOW
SENSORSINDUCTIVE
PROXIMITY
SENSORSPARTICULAR
USE
SENSORSSENSOR
OPTIONSSIMPLE
WIRE-SAVING
UNITSWIRE-SAVING
SYSTEMSMEASURE-
MENT
SENSORSSTATIC
ELECTRICITY
PREVENTION
DEVICESLASER
MARKERS

PLC

HUMAN
MACHINE
INTERFACESENERGY
CONSUMPTION
VISUALIZATION
COMPONENTSFA
COMPONENTSMACHINE
VISION
SYSTEMSUV
CURING
SYSTEMSSelection
GuideAmplifier
Built-inAmplifier-
separated**GX-F/H****GXL****GL****GX-M**GX-U/GX-FU/
GX-N**GX**


DIMENSIONS (Unit: mm in)

The CAD data in the dimensions can be downloaded from our website.


MS-GX6-1 Sensor mounting bracket for **GX-6** type (Optional)**MS-GL6-1** Sensor mounting bracket for **GX-6** type (Optional)**MS-GL6-2** Sensor mounting bracket for **GX-6** type (Optional)**MS-GXL8-4** Sensor mounting bracket for **GX-8** type (Optional)

Material: Stainless steel (SUS304)

1 pc. each of M3 (length 12 mm 0.472 in) truss head screw, nut, spring washer and plain washer is attached.

MS-GXL15 Sensor mounting bracket for **GX-15** type (Optional)

Material: SPCC

MS-A15F MS-A15H Aluminum sheet (Optional)**GX-F/H****GXL****GL****GX-M****GX-U/GX-FH/****GX-N****GX**